



MP500 V2 DSP Preset List - February 2026

Preset Number	DSP Preset Description	Amplifier Output Mode	DIP Switch Positions	2	3	4	5	6
SPEAKERS / SPEAKER SYSTEMS			*DIP Switch 1 (far left switch) toggles between Digital Coax and Optical DSP Preset DIP Switch positions begin from DIP switch 2 (2nd switch from far left)					
1	<u>Universal Flat EQ Stereo</u>	Stereo		Down	Down	Down	Down	Down
2	Installer Series ML-45AW Outdoor Speaker	Stereo		Down	Down	Down	Down	Up
3	Installer Series ML-55AW Outdoor Speaker	Stereo		Down	Down	Down	Up	Down
4	Installer Series ML-65AW Outdoor Speaker	Stereo		Down	Down	Down	Up	Up
5	Installer Series ML-75AW Outdoor Speaker	Stereo		Down	Down	Up	Down	Down
6	Outdoor Living 8.1 System STEREO (Supports up to 2 systems or subs)	Stereo		Down	Down	Up	Down	Up
7	Outdoor Living 8.1 System MONO (All speakers play the same - ideal for wide sound coverage (Supports up to 2 systems or subs)	Bridged Mono (All speakers play the same signal)		Down	Down	Up	Up	Down
8	Outdoor Living SAT 40 (Up to 4x speakers per channel)	Stereo		Down	Up	Down	Down	Down
9	Outdoor Living SAT 60 (Up to 4x speakers per channel)	Stereo		Down	Up	Down	Down	Up
10	Installer Series ML-65R Outdoor Rock Speaker	Stereo		Down	Up	Down	Up	Down
11	Installer Series ML-75R Outdoor Rock Speaker	Stereo		Down	Up	Down	Up	Up
12	Installer Series IC3-AW In-Ceiling Speaker	Stereo		Down	Up	Up	Down	Down
13	Installer Series IC8-AW In-Ceiling Speaker	Stereo		Down	Up	Up	Down	Up
SUBWOOFERS								
16	<u>Universal Flat EQ Bridged Mono</u>	Bridged Mono		Up	Down	Down	Down	Up
17	Outdoor Living Subwoofer 8 (Dual voice coils wired in parallel)	Bridged Mono		Up	Down	Up	Up	Down
18	Dual Outdoor Living Subwoofer 8 (Each subwoofers voice coils parralleled into 1 amp channel)	Bridged Mono		Up	Down	Up	Up	Up
19	Outdoor Living Dynamo Outdoor SUB 100	Bridged Mono		Up	Up	Up	Up	Down
20	Outdoor Living Dynamo Outdoor SUB 120	Bridged Mono		Up	Up	Up	Up	Up
21	Dynamo IW-S In-Wall Subwoofer	Bridged Mono		Up	Up	Down	Down	Down
22	Dual Dynamo IW-S In-Wall Subwoofers (Parrallel Wiring)	Bridged Mono		Up	Up	Down	Down	Up
23	Dynamo IW-O In-Wall Subwoofer (Open Back - No Back Box)	Bridged Mono		Up	Up	Down	Up	Down
24	Dual Dynamo IW-O In-Wall Subwoofers (Open Back - No Back Box - Parrallel Wiring)	Bridged Mono		Up	Up	Down	Up	Up
25	Dynamo IW-O In-Wall Subwoofer + Backbox	Bridged Mono		Up	Up	Up	Down	Down
26	Dual Dynamo IW-O In-Wall Subwoofers + Backbox (Parrallel Wiring)	Bridged Mono		Up	Up	Up	Down	Up