

Forte

Wireless Amplifier

SPECIFICATIONS

Amplifier Power

- 2 x 50 Watts per channel into 4 or 8 ohms (20 Hz-20kHz, 0.5%THD)
- 2 x 100 Watts per channel into 4 ohms short term peak
- 2 x 200 Watts per channel instantaneous peak

Inputs

Analog 3.5mm, Ethernet 10/100, AC Power

Wireless Inputs

Apple AirPlay®, DTS Play-Fi®

Output

Left / Right 5-way binding posts,
Subwoofer Out via Analog RCA

Wireless Connectivity

2.4 GHz and 5.0 GHz; 802.11 g/n

Room Correction

ARC™ (Anthem Room Correction) with included calibrated microphone

Power Draw

Max 170 Watts, Idle: 10 Watts, Standby: 6 Watts

Weight

3 lbs. (1.4 kg)

Size (H x W x D)

3.22" x 7.95" x 8.36" (8.2cm x 20.2cm x 21.2cm)

Specifications are subject to change without notice.



Endless variety and limitless choices. Your personal digital audio library, and your favorite online audio services, are available, wirelessly, anywhere in your home, at the touch of a button, at a level of quality that no other streaming loudspeaker system can match.

If you already enjoy a pair of MartinLogan loudspeakers you can use the Forte Wireless Amplifier to power and stream audio directly to them at the same time. Customize and optimize performance instantly with Anthem Room Correction Technology. The Forte Wireless Amplifier also features an Ethernet connection, for whole home networking up to 256 zones! When you experience it, you will agree: high quality, network-adaptable DTS Play-Fi streaming technology is the perfect high performance match for high performance MartinLogan loudspeakers.

Anthem Room Correction (ARC™) Technology is the industry's best user-controlled DSP room tuning innovation. Using advanced DSP software and a calibrated microphone, ARC tunes speaker performance to compensate for your room's unique characteristics, ensuring perfect sound in any listening space.

Forte Wireless Amplifier

